DT-398/398H

AC Leakage Current Tester











DT-398/398H clamp meters providing fast A/D converting sampling time, high accuracy offer all needed features for leakage current measurement. The are with modern bodies and jaws design for perfectly handhold and tight place testing. A clear backlit display is easy to see and a handy data hold keeps measurements on the display.

Features		
	398	398H
Accurate AC digital clamp meter for leakage current measurement		*
AC current measurement: 0 ~ 100A	*	*
AC voltage measurement: 0 ~ 600V		*
1μA ultra high resolution on 6.000 mA range		*
Shield transformer jaws to minimize the effect of external stray magnetic field.	*	*
Large jaw with 30 mm diameter.		*
ACA Six Ranges (6.000mA, 60.00mA, 600.0mA, 6.000A, 60.00A, 100A) for all application.		*
ACA Three Ranges (6.000A, 60.00A, 100A) for all application.	*	
A filter circuit is designed to eliminate the effect of high frequency noise and harmonics for AC current measurement.		*
6000 Counts LCD display (Negativity display)	*	*
Backlight for button, knob Switch & Flashlight	*	*
Pmax/Pmin, Data Hold function Temp Measurement	*	
Easy single rotary switch for any function selection		*
Continuity measurements.	*	
Frequency measurements.	*	
600V overload protection for ohm measurement	*	

Specifications							
Function	Max Range	Resolution	Basic Accuracy	398	398H		
Voltage DC	600V	0.001V	±(0.5%+2d)	*			
Voltage AC	600V	0.001V	±(1.0%+5d)				
Current AC	6.000mA, 60.00mA, 600.0mA, 6.000A, 60.00A, 100A	1μA~100mA	±(3.0%+8d)	*	*		
Resistance	60ΜΩ	0.1Ω	±(3.0%+5d)	*			
Temperature	1000°C/ 1832°F	0.1°C/1°F	±(1.0%+3d)	*			
Capacitance	99.9mF	0.001nF	±(2.5%+5d)	*			
Frequency	100kHz	0.001Hz	±(0.5%+2d)	*			
Continuity check	Buzzer sounds at 50Ω			*			
Diode test	Test Current <0.5mA MAX 3V			*			

Size(HxWxD): 239mm x 44mm x 66mm Weight: 318g

Accessories: Test leads, gift box with carrying case, temperature probe and 1.5V AAA x 3 batteries















Model 398H





Model 398