









DT-185

Light Datalogger Alarm setup and indication Recording and low battery indication Manual and automatic start mode USB port for data transmission and power supply Status indication via Red/Yellow LED and Green LED Analysis software windows 98/2000/XP/Vista/7.



Features	
Alarm setup and indication	
Recording and low battery indication	
Manual and automatic start mode	
USB port for data transmission and power supply	
Status indication via Red/Yellow LED and Green LED	
Analysis software windows 98/2000/XP/Vista/7	

Specifications	
Memory	32000 readings
Measuring rate	2sec. to 24h
Measurement Range	0 to 40 kLux/0 to 37kFc.
Measurement Max. Resolution	0.1Lux/0.1Fc.
Accuracy	±5%
Warm up period	Less than 2 seconds





Light Datalogger

Alarm setup and indication

Recording and low battery indication

Manual and automatic start mode

USB port for data transmission and power supply

Status indication via Red/Yellow LED and Green LED

Analysis software windows 98/2000/XP/Vista/7



Size(HxWxD): 145mm x 35mm x 30mm

Weight: 49g

Accessories: 3.6V Lithium battery, software and clamshell.