



DT-3348

True RMS 1000A AC Watt Clamp Meter.

DT-3348 Professional True RMS 1000A AC/DC Watt Clamp Meter provides accurate Watt, AC/DC Current and Voltage readings regardless of waveforms.



DC/AC True Power to 240kW



1000A True RMS

Features
True RMS AC Voltage and Current
DC and AC True Power to 240kW
1.2" (30mm) Clamp jaw opening
Electronic overload protection
Continuity buzzer & Diode check
Data Hold function
DCA Zero function
Auto Power Off
Low battery indication
AC/DC Current

Size (H x W x D): 229mm x 80mm x 49mm

Weight: 303g

Specifications			
Function	Max Range	Max. Resolution	Basic Accuracy
AC Current	1000 A	0.1A	±(2.5%+5d)
DC Current	1000 A	0.1A	±(3.0%+4d)
AC Voltage	600V	0.1mV	±(0.8%+2d)
DC Voltage	600V	0.1mV	±(1.0%+4d)
Resistance	40MΩ	0.1Ω	±(1.0%+4d)
Frequency	10MHz	0.01MHz	±(1.2%+3d)
AC Power	240kW	10W	±(3.0%+5d)
DC Power	240kW	10W	±(2.5%+5d)

Applications



True RMS 1000A AC Watt Clamp Meter.

DT-3348 Professional True RMS 1000A AC/DC Watt Clamp Meter provides accurate Watt, AC/DC Current and Voltage readings regardless of waveforms.



• 1000A True RMS

• DC/AC True Power to 240kW

Accessories: Test leads, gift box with carrying case & 9V battery